

CA22C3BK
REFILL INSTRUCTIONS
For Canon® BC-22 PHOTO

Contents:

Your kit should contain the following:

4 - 2oz bottles of ink, 1 10cc syringe, 1 blunt needle, 2 cotton wipes, 1 drill tool, instructions.

If any of these items are missing please call us for a replacement item or kit.



PLEASE WORK ON NEWSPAPER IN CASE OF SPILLAGE

**** Please read the entire set of directions before proceeding.**

- 1) Remove the BC-22 cartridge from your printer. Please do NOT touch the printhead as this may cause permanent damage to the cartridge.
- 2) Locate the four vent holes on the cartridge as illustrated in figure 1. Use the drill tool provided to drill through the vent hole of the plug associated with the color ink you want to refill. Drill all the way through the plug and by slightly bending the tool pull out the plug. Save the plug.
- 3) Attach the needle to the syringe and draw 12cc of black ink from the bottle. Insert the needle into the hole where you removed the plug. Make sure you are injecting the correct color ink into the vent hole. Refer to figure 1. For the colors use 4cc of ink in each chamber.
Insert the needle as far as it can go into the chamber and inject the ink SLOWLY while pulling the needle out. It's helpful to place some electrical tape over the other holes to avoid contamination.
- 4) Re-insert the plug (removed in step 2) into the vent hole. Install the cartridge into your printer and run the printer's head cleaning routine a few times.




figure 1